SWIT® UC-2120 120W USB-C/A GaN Charger Ver:A

USER MANUAL

SWIT Electronics Co., Ltd.

Tel:+86-25-85805753 Fax:+86-25-85805296 http://www.swit.cc E-mail: contact@swit.cc

Thank you for choosing SWIT products. Please read the instructions before using, and keep it for future reference.

A Warning

Keep in mind the following precautions to avoid fire or electric shock!

- Never expose the battery charger to rain or moisture.
- Never attempt to open the battery charger, please contact the local agent if have problems.
- Never use metal or other conductors to touch the inside of the battery charger.
- Please make sure the voltage range is fit for the battery charger.

Appearance

П

ⓓ

100W Max \square 100W Max -(4) 36W Max

① Power plug: EU and UK standard for option

- 2 USB Type C output 1, Max 100W
- ③ USB Type C output 2, Max 100W
- ④ USB Type A output 1, Max 36W
- (5) USB Type A output 2, Max 36W

Specifications

Input voltage (Nominal)	AC 100~240V, 50/60Hz	
Input voltage (Range)	AC 90~264V	
Output Power	120W Max	
USB-C only	USB-C: PD 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/5A	Max 100W
USB-A only	USB-A: 4.5V/5A, 5V/3A, 9V/3A, 12V/3A, 20V/1.5A	Max 36W
USB-C + C	USB-C: PD 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/3A	Max 60W+60W
USB-A + A	USB-A: 5V/3A	Max 15W in total
USB-C + A	USB-C: PD 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/5A USB-A: 5V/3A, 9V/2A, 12V/1.5A	Max 100W+18W
USB-C + C + A	USB-C: PD 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/2.25A USB-A: 5V/3A, 9V/2A, 12V/1.5A	Max 45W+45W+18W
USB-C + A + A	USB-C: PD 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/5A USB-A: 5V/3A	Max 100W+15W
USB-C + C + A + A	USB-C: PD 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/2.25A USB-A: 5V/3A	Max 45W+45W+15W
Working Environment	Temperature -10°C to 40°C; Humidity 10%RH to 90% RH	
Storage Environment	Temperature -10°C to 85°C; Humidity 10%RH to 90% RH	
Dimension	77.3mm × 60.5mm × 31.5mm	
Weight	255g	

Caution

(2)

(3)

(5)

- Keep the terminals clean and ensure the reliable connection.
- It is a normal phenomenon that the battery charger may become warm in use.
- Do not cover the cooling vent.
- Please do not cover the charger when it's charging.
- The charger works between -10°C to 40°C. However, we recommend that use the charger between 0°C to 25°C to ensure highest efficiency.