
# **SVIT**®







SWIT's professional LED solutions are tailored for applications such as film, television, broadcasting, and mixed reality (XR), giving you complete control to ensure exceptional and consistently high-quality lighting effects.




#### **Specifications**

	MONET-400	MONET-700
Power	400W MAX	700W MAX
nput Voltage	AC 100-240V, 50/60Hz, DC 48V	
RI	≥95	
LCI	≥95	
SI	75 @ D55	
olor Temp	2800-10000K with G/M adjustment	
ontrol	On-board, SWIT Console App, 5-Pin DMX512, RadioLux (Optional), LumenRadio CRMX	
mming	0-100%, stepless 0.1% from 0.1 to 100%	
ate	IP20	
etime	50,000 hours	
Size	357.0mm x 353.6mm x 170.4mm	623.2mm x 353.6mm x 170.4mm
	Approx. 13.25" x 13.57" x 6.67"	Approx. 24.46" x 13.57" x 6.67"
unting	Strong filter mounting bracket	Strong filter mounting bracket
t Weight	7.8 kg / 17.2 lbs	15.2 kg / 33.51 lbs




















## 3.5-inch Color LED On-Board Control



**CCT Control** 





HOME

X: 0.131 0.046







255 . 255 . 255 . 000

**RGB** Control

CIE Control

**Light Effects** 

**GEL Selection** 

Art-Net IP Setting



# **Brighter RGB Color Light**

Time-Division Drive Tech (Patented)

The regular RGB panels are high bright in CCT mode, but much lower in RGB color mode. That's because in a regular RGB light, the RGB color LED and White LED have fixed rates to share the total power of the light, and when output color lights, the RGB LEDs use only

MONET RGB lights adopt SWIT unique Time Division Drive tech, full power of the light can be assigned to R/G/B color LEDs, and greatly increased the intensity of color light.



# **Precision Light Control**

Stepless 0.1% from 0.1 to 100%

MONET employs precise 0.1% incremental adjustment, allowing you to start from zero and smoothly adjust the brightness of the light.



### Variety of accessories

Quick-mount system

MONET is equipped with a quick-mount accessory system. All accessories are easily installed.





#### **Bluetooth App**

Available for Android and iOS

SWIT Console, now includes support for MONET. It consolidates all functions into one, offering a comprehensive alternative to onboard controls.








#### **Illuminance and Light Quality Parameters**

High-Quality White Light and Color Light

\*All data collection is paired with a diffuser







TM-30 RF (Average) 95 TM-30 RG (Average) 104

